

marantz®



MODEL 30

Marantz MODEL 30 Integrated Amplifier

Get the most musical sound possible from this beautiful, integrated amplifier. Exquisitely tuned by the Marantz Sound Master, the MODEL 30 integrated amplifier features a master-curated Marantz HDAM and a fully discrete design for luxurious Hi-Fi purity. Designed to last the test of time and make all your music unforgettable.

- Custom-built preamplifier with Marantz HDAM technology.
- Tuned with passion by the Marantz Sound Master.
- Output: 100W + 100W (8ohm), 200W + 200W (4ohm).
- Fully-discrete design for signal purity.
- Custom HDAM®-SA3 circuitry for clean, optimal dynamics.
- Separate amp and preamp power supplies reduce interference.
- Toroidal transformer dedicated to preamp for clarity and power.
- Current feedback preamp design with its wide-range circuitry.
- MM/MC Phono input with its Premium Phono EQ circuit.
- Brass machined input terminals for CD and Phono.
- Marantz original high-quality/high-purity copper speaker terminals.
- Linear volume control with new electric volume system.
- Amplifier design inherited from our flagship models.
- Available in Black and Silver Gold.



Modern Musical Luxury



MODEL 30

Technical Specifications



| | |
|------------------------------------------|-------------------------------------------------------------------------------------------------------------------------|
| Output Power | |
| Rated Output Power | 100W + 100W (8ohm) 200W + 200W (4ohm) |
| Features | |
| Amplifier Circuit | Switching Amplifier |
| Power Transformer | Toroidal w/ case |
| Volume | Electric |
| Bass / Treble / Mid / Balance Control | yes / yes / - / yes |
| Source Direct | yes |
| Wide Range | 5Hz - 50kHz |
| Total Harmonic distortion | 0.005% (1kHz, 8Ω) |
| Damping Factor | 500 |
| Input Sensitivity: Phono input | MM: 2.3 mV / 39 kohm MC: 250 μV / 100 ohm |
| Input Sensitivity: CD/LINE/RECORDER | 220 mV / 13 kohm |
| Input Sensitivity: Power Amplifier input | 1.1 V / 13 kohm |
| SN Ratio | PHONO (MM): 88dB PHONO (MC): 75dB CD: 107dB |
| Terminal | |
| Phono Input | yes (MM/MC) Marantz Musical Premium Phono EQ |
| Ext. Pre Input (Power Amp Direct) | yes |
| Preout | yes |
| Audio (In/Out) Terminals | 6/1 (PHONO / MM&MC / CD / TUNER / LINE 1 / LINE 2 / RECORDER) * [PHONO] and [CD] inputs = high grade terminals |
| Speaker Terminal | Marantz Original SPKT-100+ |
| Remote Control Bus Terminal | yes (Cinch) |
| UI | |
| Display | yes (Porthole, OLED) |
| Control | |
| App Control via Network Player | yes |
| System Remote Controller | yes (New system remote controller to control SACD 30 and MODEL 30) |

| | | | |
|--------------------------------------------|----------------------------|--------------|-------------|
| Other | | | |
| Unit (W x H x D mm) | 443 x 130 x 432 | | |
| Packaging Dimensions (W x H x D mm) | 534 x 255 x 522 | | |
| Net weight | 14.8kg | | |
| Packaging gross weight | 17.6kg | | |
| Unit (W x H x D in inches) | 17.4" x 5.1" x 17" | | |
| Packaging Dimensions (W x H x D in inches) | 20" x 10.1" x 20.6" | | |
| Weight | 32 lbs 3 Oz | | |
| Packaging Weight | 37 lbs 8 Oz | | |
| Power Consumption | 130W | | |
| at Standby | 0.2W | | |
| AC Inlet | yes | | |
| Quick Start Guide | Paper | | |
| Cosmetic | | | |
| Panel Color | SG / BK | | |
| Front Center Panel | Aluminum | | |
| Side cover | Aluminum | | |
| Top cover | Steel | | |
| Edge-lighting | yes (Dimmer) | | |
| Volume Knob | Aluminum | | |
| Input Selector | Aluminum | | |
| Bass/Treble/Balance/ REC Out Sel knobs | REC Out-->PHONO (Aluminum) | | |
| Power button | Aluminum | | |
| Side screw | Copper plated | | |
| Chassis Material | SECC | | |
| Chassis Layer | Triple | | |
| Foot | New (PM6006 type) | | |
| UPC | | | |
| USA | MODEL30/U1B | 699927170059 | Black |
| USA | MODEL30/U1SG | 699927170158 | Silver Gold |

Design and specifications are subject to change by Marantz without notice.

www.marantz.com

