

PULSE SUB



Small and Easy to Live With. With the PULSE SUB, Bluesound has reimagined the subwoofer. Most subwoofers are large cubes that don't often fit very well in the typical living room. The PULSE SUB on the other hand, is a compact, slim, rectangular shape, allowing it to fit beside, behind, or underneath living room furniture. This room friendly design has several clever installation options.

PULSE SOUNDBAR, meet PULSE SUB

The wireless transmitter in the PULSE SOUNDBAR automatically senses the presence of the PULSE SUB and adjusts its internal settings to redirect the lowest bass notes wirelessly to the wireless subwoofer. There is also the option of a wired connection as well. Perfect acoustic alignment in the crossover region is easily dialed in with the BluOS App for smartphones, tablets and laptops.

100 TOTAL WATTS DYNAMIC PEAK
WIRELESSLY PAIRS WITH
PULSE SOUNDBAR
SUB VOLUME CONTROL
SUB CROSS OVER CONTROL
SUB PHASE CONTROL
LOW-LEVEL ANALOG INPUT & OUTPUT
LFE INPUT & OUTPUT
0.5W STANDBY MODE
BLACK FINISH

165MM POWERED SUBWOOFER

Place it Anywhere, Above or Below

A wall mount bracket is included to allow the PULSE SUB to be located almost anywhere in the room; no need to use up valuable dance floor space. All mounting hardware (screws not included) and simple instructions are included. The innovative rubber feet can also be used to stand the PULSE SUB vertically for placement behind or beside a sofa or chair, or it can be placed horizontally underneath a couch or end table.

Digs Deep and Plays Loud

The PULSE SUB may be small and room friendly, but it is also a full-fledged subwoofer carefully engineered to pump out prodigious quantities of well-defined, low distortion bass. With 100W of power from its cool running and highly efficient amplifier, there is plenty of power on tap to add weight to your favorite music, as well as excitement to your favorite movie soundtracks. Variable crossover frequency and phase alignment, along with volume adjustment allows the PULSE SUB to be used with any system, not just the PULSE SOUNDBAR. There is also a wired connection option that can easily connect to any amplifier with a subwoofer output.









PULSE SUB Specifications

Features:

Controls: Volume Control, Variable Frequency, Variable Phase 0° - 180°,

Standby Control Switch, Pairing Mode Switch

Connections: Low/Line Level Inputs & Outputs

LFE Inputs & Outputs 100V-240V, 50/60Hz

Universal Voltage: 100V-240V, 50/60Hz Energy Star Compliance: 0.5w Standby

Frequency Range:

Response:

On Axis @ 0°±3dB: 26Hz - 150Hz

Off Axis @ 30°±3dB:

LF Cutoff -10dB: 20Hz

Amplifier Power:

Continuous: 100w
Dynamic: 100w
Dynamic Peak: 200w
Type: CLASS D

Accoustic Design:

Woofer (Nominal): 6 1/2" (165mm) Polyproplene cone, Elliptical Surround

Crossover: 50Hz - 150Hz

Finish: Black

Dimensions (Unit):

(W x H x D) 447mm x 285mm x 122mm (17.6" x 11.25" x 4.8")

(not including feet or wall bracket)

Weight: 15.25 lbs

Included Accessories: 120V AC Power Cord 230V AC Power Cord Wall Mount Bracket

2 Attachable Feet for Floor Stand Safety/Warranty Guide

Quick Setup Guide

