

9.2-ch Network AV Receiver

VSX-LX504(B/S)





The VSX-LX504 creates the soundscape of IMAX® Enhanced*1 and Dolby Atmos*/DTS:X ideally calibrated with Advanced MCACC, and even provides similar sound effects with Dolby Atmos Height Virtualizer*1 without height or surround speakers. Enjoy spectacles from next generation video standards with support for HDCP 2.2, or stream songs across the house with SONOS system, FlareConnect™, Chromecast built-in, DTS Play-Fi®, and Apple AirPlay 2. Other features include Powered Zone 2/Zone 3 Audio, up to 11.2 MHz DSD direct playback, and 2 HDMI outputs.

AMPLIFICATION

- > Channels: 9
- > Amplification Type: Direct Energy
- > 215 W/ch (6 ohms, 1 kHz, THD 10 %, 1ch Driven)
- > 180 W/ch (8 ohms, 1 kHz, THD 1 %, 1ch Driven IEC)

AUDIO FEATURES

- > IMAX Enhanced*1
- > Dolby Atmos*, Dolby Surround Upmixer
- > DTS:X°, DTS Neural:X° Upmixer
- > Reflex Optimizer
- Dolby Atmos Height Virtualizer*1
- > Dolby TrueHD, Dolby Digital Plus
- DTS-HD Master Audio, DTS-HD High Resolution Audio, DTS 96/24, DTS-ES, DTS Express
- > DSD Direct Playback via Network/USB (11.2, 5.6, 2.8 MHz/2 ch)
- > DSD Disc (SACD) Playback via HDMI (2.8 MHz/2 ch, 5.1 ch)
- ➤ Digital Quad-Core 32-bit DSP (Cirrus Logic) + Aureus[™] floating-point DSP (TI)
- 384 kHz/32-bit D/A Conversion with AK4458 (AKM) & PCM5101A (TI)
- > Enhanced Audio Return Channel (eARC) on HDMI
- > Advanced MCACC Auto Room Tuning
 - · Auto Phase Control Plus
 - Subwoofer EQ
 - · Multi-point Standing Wave Control
- > Advanced Sound Retriever (2ch)
 - Advanced Surround Modes
 - Classical, Unplugged, Entertainment Show, Drama, Advanced Game, Action, Rock/Pop, Sports, Extended Stereo, Extended Mono, Front Stage Surround Advance

VIDEO FEATURES

Ultra HD Pass-through with HDCP 2.2 (4K/60p/4:4:4/24-bit, 4K/24p/4:4:4/36-bit, 4K/60p/4:2:0/36-bit)*2

- HDR10, HLG and BT.2020 Compliant Wide Colour Gamut Signal Pass-through
- > Dolby Vision™ Compatible
- > Ultra HD Upscaling (1080p to 4K)
- 3D Ready (Blu-ray Disc™, Broadcast, and Games)
- > Deep Colour (36-bit), "x.v. Colour"

HOME NETWORK FEATURES

- > FlareConnect[™] for Multi-room Audio
- > Chromecast built-in*3 and Works with the Google Assistant
- > DTS Play-Fi with Pioneer Music Control App
- Apple AirPlay 2
- > Works with SONOS
- Amazon Music, Spotify, TIDAL, and Deezer Hi-Fi Music-Streaming Services Ready*4
- > Internet Radio with TuneIn
- > Hi-Res Audio File Playback via USB/Network
 - Up to 192 kHz/24-bit ALAC*5, AIFF, FLAC, WAV (RIFF) and 11.2 MHz DSD*6

CONVENIENCE FEATURES

- > Personal Preset
- Dialog Enhancement
- > Dual Band (5 GHz/2.4 GHz) 802.11ac Compliant Wi-Fi* Built-in
- > Bluetooth* Wireless Technology (Version: 4.2 + LE, Profile: A2DP 1.2/AVRCP 1.3, Codec: SBC/AAC) Built-in
- Pioneer Remote App*7 Ready for Multi-room Entertainment Control and Network Streaming
- User-Friendly GUI with System Setup Menu
- > On-Screen Information for Audio/Video Status
- > PC Setu
- > Auto Power Off in HDMI Standby Through
- > AM/FM Tuner 40 Presets
- > Sleep Timer
- > User-Friendly Simple Remote Control

FRONT TERMINALS

- > HDMI 1 In
- > USB 1 In for USB Drive
- > MCACC Setup MIC In
- > Phones 1 Out

REAR TERMINALS

- > HDMI 6 In (4 Assignable)
- > HDMI 2 Out (1 for MAIN, 1 for SUB)
- > Ethernet 1 In
- > USB 1 In for USB Drive
- > AV (Component) 1 In (Assignable)
- > AV (Composite) 2 In (Assignable)
- > Audio 1 In (Assignable)
- > Phono (MM) 1 In

- > Digital Coaxial 1 In (Assignable)
- > Digital Optical 1 In (Assignable)
- FRONT, CENTER, SURROUND, HEIGHT 1, SURROUND BACK, SUBWOOFER x 2 Pre Out
- > ZONE B Line Out for Wireless Headphones
- ZONE 2 Pre/Line Out, ZONE 3/HEIGHT 2 Pre/Line Out
- > Speaker 11ch Out (FRONT, CENTER, SURROUND, HEIGHT 1/Bi-AMP, SURROUND BACK/HEIGHT 2/ZONE 3, ZONE 2)
- > IR 1 In/1 Out
- > 12 V Trigger 2 Out
- > RS-232C
- > FM/AM Antenna

SPECIFICATIONS

- > Power Requirements: AC 220-240 V, 50/60 Hz
- Power Consumption/Standby: 870 W/ 0.15 W
- Dimensions (W x H x D): 435 x 185 x 386 mm
- > Weight: 13 kg

^{*}¹ Available with future firmware update *² Except AUX INPUT (Front) *³ Chromecast-enabled apps required *⁴ Service availability depends on country or region *⁵ Up to 96 kHz supported via wireless LAN *6 Not guaranteed via wireless LAN *7 Available for free download from the App Store/The Google Play



VSX-LX504(B)/MMP

IMAX Enhanced*

The VSX-LX504 is IMAX Enhanced, certified to deliver the powerful sound just as intended by the filmmaker, and provide the immersive experience on your home theater.



* Function available with future firmware update

Dolby Atmos®/Dolby Surround Upmixing

By adding an external amplifier, the 9.2ch AV receiver can be expanded to decode 11ch to drive the 7.2.4ch



configuration of Dolby Atmos*. You can reproduce object-oriented sound in smooth, curving movements, or the realistic threedimensional movement overhead by the top speakers. Other audio codecs such as PCM and DSD can be upmixed using Dolby Surround for enjoying 3D surround sound.

Dolby Atmos 7.2.4ch Speaker System



DTS:X[®]/DTS Neural:X Upmixing

DTS:X is the next-generation audio codec from DTS that leverages object-based audio to enable new immersive and interactive audio experiences. By adding an external amplifier, the 9.2ch AV receiver can be expanded to decode 11ch for driving a 7.2.4ch surround system. Experience an immersive soundscape with incredibly rich and life-like audio. Other audio codecs such as PCM and DSD can be upmixed using DTS Neural:X for enjoying 3D surround sound.

DTS:X 7.2.4ch Speaker System



Dolby Atmos Height Virtualization*

When playing any Dolby format, engaging the Dolby Atmos Height Virtualizer enables a more immersive listening experience, creating a virtual surround and height effect from traditional speaker layouts without employing additional surround or height speakers.

Function available with future firmware update

Apple AirPlay 2

Apple AirPlay 2 lets you effortlessly stream music or podcasts to speakers throughout your house using any Apple device or by asking Siri, and it all stays in perfect svnc.



Next Generation Video Standard Ready

The VSX-LX504 supports pass-through for HDR10, HLG (Hybrid Log-Gamma), and Dolby Vision signals. By connecting a





compatible source device, you can enjoy these latest video standards on a compatible display. What's more, all HDMI terminals support 4K (60p/4:4:4/24-bit), Wide Colour Gamut (BT.2020), and HDCP 2.2, so you will have no problem when upgrading to new devices, and can also enjoy premium content such as 4K videos with digital copy protection.

HDR Dynamic Range Expansion Image





For illustration purpose only

Advanced MCACC Auto Room Tuning featuring Auto **Phase Control Plus**

Advanced MCACC adjusts the sound according to the listening room and speakers, and also creates clearer sound by suppressing the standing waves that occur between walls or ceiling and floor. Measurement of up to nine positions can be saved for a wide listening area. Auto Phase Control Plus* makes real-time analysis of the phase difference, and automatically compensates the gap between the LFE and main signals, providing strong bass and clear high-frequency sound.

* Effectiveness depends on content

Works with SONOS

By connecting the VSX-LX504 to Sonos Connect, you can play any music or audio source on your Sonos SONOS app. You can group the VSX-LX504 with other Sonos devices on the network, or use it independently. The AV receiver will automatically turn on and switch input as soon as you play music on your Sonos app.

Powered Zone 2/Zone 3

With the powered feature, the VSX-LX504 can directly drive speakers in other rooms, without the need for a separate amplifier. What's more, the dedicated DAC for Zone 2 lets you listen to all digital audio sources.



Zone B Output for Wireless Headphones

The VSX-LX504 is equipped with Zone B audio output. The Zone 2 Pre output can also used as Zone B Line output to extend the sound of Zone A (Main Zone) to another location or to wireless headphones via a transmitter.



Chromecast built-in

The VSX-LX504 comes with Chromecast built-in, so you can use your mobile device to stream your favorite music, radio, or podcasts to your speaker. You can control the audio from anywhere in the house using Chromecast-enabled apps running on your personal device—iPhone, iPad, Android





phone and tablet, Mac and Windows laptop, and Chromebook™. The VSX-LX504 also works with the Google Assistant, so you can tell it to turn up the volume, skip tracks, or stop the music using your Google Assistant enabled device, like Google Home. Discover Chromecastenabled apps at google.com/cast/apps



















































PIONEER,MCACC,PhaseControl,AdvancedSoundRetriever,andthelogosareregisteredtrademarksofPioneerCorporation,andareusedunderlicense.-ThetermsHDMlandHDMlHigh-DefinitionMultimediaInterface,and theHDMlLogoaretrademarksorregisteredtrademarksofPioneerCorporation,andareusedunderlicense.-ThetermsHDMlandHDMlHigh-DefinitionMultimediaInterface,and theHDMlLogoaretrademarksofDolby,DolbyAtmos,DolbySurround,DolbyVision,andthedouble-Dsymbolareregistered trademarksofDolbyLaboratories.-ManufacturedunderlicensefromIMAXCorporation.IMAX'isaregisteredtrademarkoflMAXCorporationinthe UnitedStatesand/orothercountries.AllightsReserved.ForDTS,Inc.DTS,theSymbol,DTSandtheSymboltogether,DTS:X,Play-Fi,theDTS:Xlogo,andtheDTSPlay-Filogo,areregisteredtrademarksortrademarksofTDS,Inc.in the UnitedStatesand/orothercountries. DTS,Inc.AllRightsReserved.-Apple,AirPlay,iPhone,iPad,Mac,andSiriaretrademarksofAppleInc.,registeredintheU.S.andothercountries.-Apple.Air-Iliance.TheWi-FiCERTIFIEDLogoisacertificationmarkoftheWi-FiAlliance.-TheBluetooth wordmarkandlogosareregisteredtrademarksowned byBluetoothSiG,Inc.-*x.v.Colour*isatrademarksofSonyCorporation.-SpotifylogoaretrademarksoftheSpotifylogoaretrademar is not available in certain languages or countries. Controlling certain devices in your home requires compatibles mart devices. Subscriptions for services and applications may be required and additional terms, conditions and/or example of the contraction ofcharges may apply